

CH16B-1

Type Size: S1

Classification Contact: Rigid contact bridge

Classification Contact Mat: Gold

Classification Terminal: Screw terminal

IEC 60947-3 EN 60947-3, VDE 0660 Teil 107

Rated insulation voltage Ui				
		Voltage (V)		AC / DC
		690	AC	
Rated impulse withstand voltage Uimp				
Voltage (kV)	Overtoltage category	Pollution degree	Supply system	Function
6	III	3	Valid for lines with grounded common neutral termination	Switch
Rated uninterrupted current Iu/Ith				
Current (A)	Ambient temperature (°C)	Peak temperature (°C)	additional requirements	
20	55	60	Ambient temperature +55°C during 24 hours with peaks up to +60°C	
Rated operational current Ie				
Utilization category				Current (A)
AC-15	220 - 240			2,50
AC-15	380 - 440			1,50
AC-21A	12 - 690			20
Max. Fuse rating IEC				
Fuse characteristic				No. of Fuses
gG				1
				20

GENERAL TECHNICAL INFORMATION

Tightening torque of screws				
		tightening torque (Nm)	tightening torque (lb-in)	
		1	9	
Rated short-time withstand current Icw				
			Current (A)	
			165	
Size of conductor				
composition of conductor	Min. / Max. value	No. of conductor per terminal	Cross section (mm ²) or (AWG/kcmil)	Material of the wire
Flexible wire	Max.	2	AWG 12	Copper
Flexible wire	Max.	2	2.5mm ²	Copper
Single-core or stranded wire	Max.	2	AWG 10	Copper
Single-core or stranded wire	Max.	2	4mm ²	Copper
Flexible wire with ferrule according to DIN 46228	Max.	2	2.5mm ²	Copper

Approbations	
Specification	Marking
CE marking	
UK Directives	

IEC 60947-3; EN 60947-3; VDE 0660 Teil107

IEC 60947-3
EN 60947-3

Power loss per pole	
Power (W)	
1,80	

Conditions during transport and storing			
Minimum temperature (°C)	Maximum temperature (°C)	additional requirements	
-40	85	In case of temperatures below -5°C no shock load permissible	

General Information	
Text	

- Terminals with factory fitted jumper links are tightened during production for loss prevention. When opening the terminal clamps, make sure that no factory fitted links get lost and that all wire connections are properly seated.

General Information*Text*

- After wiring, ALL terminal screws must be tightened to the specified torque values.
- The protection class of the selected mounting type may vary if optional extras are used.
- Do not lubricate or treat contacts.
- Switches may only be mounted, connected and set into operation by qualified persons according to the accepted rules of technology.
- After installation of the switches the spacings between the terminals must be sufficient to fulfill the requirement of the applicable standards.

Operating temperature*Min. Temperature [°C]*

-25

Max. Temperature [°C]

60