

## FA4

Type Size: S0

Classification Contact: Rigid contact bridge

Classification Contact Mat: Silver

Classification Terminal: Screw terminal

### IEC 60947-3 EN 60947-3, VDE 0660 Teil 107

Rated insulation voltage Ui				
		Voltage (V)		AC / DC
		440		AC / DC
Rated impulse withstand voltage Uimp				
Voltage (kV)	Overvoltage category	Pollution degree	Supply system	Function
4	III	3	Valid for lines with grounded common neutral termination	Switch
Rated uninterrupted current Iu/Ith				
Current (A)	Ambient temperature (°C)	Peak temperature (°C)	additional requirements	
10	55	60	Ambient temperature +55°C during 24 hours with peaks up to +60°C	
Rated operational current Ie				
Utilization category				Current (A)
AC-15	110 - 120			2,50
AC-15	220 - 240			2,50
AC-15	380 - 440			1,50
AC-20A	440			10
AC-21A	440			10
AC-22A	220 - 240			10
Max. Fuse rating IEC				
Fuse characteristic				Current (A)
gG	1			10

### GENERAL TECHNICAL INFORMATION

Tightening torque of screws				
		tightening torque (Nm)	tightening torque (lb-in)	
		0,40	3,50	
Rated short-time withstand current Icw				
		Time (s)	Current (A)	
		1	60	
Size of conductor				
composition of conductor	Min. / Max. value	No. of conductor per terminal	Cross section (mm <sup>2</sup> ) or (AWG/kcmil)	Material of the wire
Flexible wire	Max.	2	AWG 16	Copper
Flexible wire	Max.	2	1.5mm <sup>2</sup>	Copper
Single-core or stranded wire	Max.	2	AWG 14	Copper
Single-core or stranded wire	Max.	2	1.5mm <sup>2</sup>	Copper
Flexible wire with ferrule according to DIN 46228	Max.	2	1mm <sup>2</sup>	Copper

Approbations	
Specification	Marking
CE marking	
UK Directives	
IEC 60947-3; EN 60947-3; VDE 0660 Teil107	<b>IEC 60947-3</b> <b>EN 60947-3</b>
UL 60947-4-1; CSA C22.2 No. 60947-4-1	
CSA C.22.2 No.14	

Power loss per pole	
	<i>Power (W)</i>
	0,40

Conditions during transport and storing		
<i>Minimum temperature (°C)</i>	<i>Maximum temperature (°C)</i>	<i>additional requirements</i>
-40	85	In case of temperatures below -5°C no shock load permissible

**General Information**

*Text*

- Use only copper wires with or without tinned/silver-plated individual wires. Soldering the end of the wire before wiring is not allowed.
- Terminals with factory fitted jumper links are tightened during production for loss prevention. When opening the terminal clamps, make sure that no factory fitted links get lost and that all wire connections are properly seated.
- After wiring, ALL terminal screws must be tightened to the specified torque values.
- The protection class of the selected mounting type may vary if optional extras are used.
- Do not lubricate or treat contacts.
- Switches may only be mounted, connected and set into operation by qualified persons according to the accepted rules of technology.

Operating temperature	
<i>Min. Temperature [°C]</i>	<i>Max. Temperature [°C]</i>
-25	60