



Text

KG10A

Type Size: S0

Classification Contact: Rigid contact bridge

Classification Contact Mat: Silver

Classification Terminal: Screw terminal

IEC 60947-3 EN 60947-3, VDE 0660 Teil 107 Rated insulation voltage Ui Voltage (V) AC / DC 690 AC Voltage (kV) Overvoltage category Pollution degree Supply system Function Switch / Switch 3 Valid for lines with grounded common neutral termination disconnector Rated uninterrupted current lu/lth Current (A) additional requirements Ambient temperature (°C) Peak temperature (°C) Ambient temperature +50°C during 24 hours with peaks up to +55°C 20 50 55 No. of stages (from - to) Ambient temperature Peak temperature (°C) Additional requirements Mounting Mounting size Ambient temperature +35°C during 24 hours with peaks up to +40°C $\,$ 20 35 Rated operational current le Utilization category Voltage (V) Current (A) AC-15 220 - 240 6 AC-15 380 - 440 4 AC-20A 690 20 AC-21A 20 - 690 20 AC-22A 220 - 500 20 AC-22A 660 - 690 16 Rated operational power Utilization category No. of phases No. of poles Power (kW) Voltage (V) AC-3 220 - 240 3 3 2.20 AC-3 380 - 440 3 3 3,70 AC-3 500 - 500 3 3 3.70 AC-3 660 - 690 3 3 3,70 220 - 240 AC-3 2 1.10 AC-3 380 - 440 2 1,50 AC-23A 220 - 240 3 3 3 AC-23A 380 - 440 3 3 5,50 500 - 500 AC-23A 3 3 5,50 AC-23A 660 - 690 3 3 5,50 AC-23A 220 - 240 1,50 380 - 440 2,20 AC-23A 2 Max. Fuse rating IEC No. of Fuses Current (A) αG 20 UL60947-4-1, UL508 Voltage (V) AC / DC 300 AC Current (A) Ambient temperature (°C) Additional Text 20 0 - 40

- The operating handle and position indicating means to be used with these manual motor controllers should be provided from the manufacturer, or the operating handle and position indicating means to be used should have been previously evaluated in combination with the manual motor controllers.



General Information

Text

- When intended for use as a motor disconnector the device shall be provided with a method of being locked in the OFF-position.

20

CSA

Rated insulation voltage Ui

Voltage (V) AC / DC

300 AC

Rated thermal current

Current (A)

Ambient temperature (*C)

Additional Text

GENERAL TECHNICAL INFORMATION

Tightening torque of screws

tightening torque (Nm)
tightening torque (lb-in)
0,60

Rated short-time withstand current lcw

0 - 40

 Time (s)
 Current (A)

 1
 130

		!		100
Size of conductor				
composition of conductor	Min. / Max. value	No. of conductor per terminal	Cross section (mm²) or (AWG/kcmil)	Material of the wire
Solid wire	Min.	1	0.5mm²	Copper
Solid wire	Min.	2	0.5mm²	Copper
Flexible wire	Min.	1	0.75mm²	Copper
Flexible wire	Min.	2	0.75mm²	Copper
Flexible wire	Max.	1	AWG 12	Copper
Flexible wire	Max.	1	2.5mm²	Copper
Single-core or stranded wire	Max.	1	AWG 12	Copper
Single-core or stranded wire	Max.	1	2.5mm²	Copper
Flexible wire with ferrule according to DIN 46228	Max.	1	2.5mm²	Copper
Flexible wire with ferrule according to DIN 46228	Min.	1	0.5mm²	Copper
Flexible wire with ferrule according to DIN 46228	Min.	2	0.5mm²	Copper

Specification Marking
CE marking

UK Directives

Approbations

IEC 60947-3; EN 60947-3; VDE 0660 Teil107

EN 60947-3

EN 60947-3

UL 60947-4-1; CSA C22.2 No. 60947-4-1



CSA C.22.2 No.14



Power (W) 0,90

Power loss per pole

Conditions during transport and storing

Minimum temperature (°C)

-40

Maximum temperature (°C)

-40

85

In case of temperatures below -5°C no shock load permissible

Shock / Vibration

Type of oscillation

Values

Resistance to vibration IEC 61373 (1999) Category 1, Class B

General Informa

Text

- Use only copper wires with or without tinned/silver-plated individual wires. Soldering the end of the wire before wiring is not allowed.
- Terminals with factory fitted jumper links are tightened during production for loss prevention. When opening the terminal clamps, make sure that no factory fitted links get lost and that all wire connections are properly seated.
- After wiring, ALL terminal screws must be tightened to the specified torque values.
- The protection class of the selected mounting type may vary if optional extras are used.
- Do not lubricate or treat contacts.
- Switches may only be mounted, connected and set into operation by qualified persons according to the accepted rules of technology.





General Information

Text

- After installation of the switches the spacings between the terminals must be sufficient to fulfill the requirement of the applicable standards.

 Operating temperature
 Min. Temperature [°C]
 Max. Temperature [°C]

-25 55