



Sample image

KG10

Type Size: S0

Classification Contact: Rigid contact bridge

Classification Contact Mat: Silver

Classification Terminal: Screw terminal

IEC 60947-3 EN 60947-3, VDE 0660 Teil 107

Rated insulation voltage Ui

Voltage (V) AC / DC

690 AC

Rated impulse withstand voltage Uimp

Voltage (kV)	Overvoltage category	Pollution degree	Supply system	Function
4	II	3	Valid for lines with grounded common neutral termination	Switch / Switch disconnector

Rated uninterrupted current Iu/Ith

Current (A)	Ambient temperature (°C)	Peak temperature (°C)	additional requirements
20	50	55	Ambient temperature +50°C during 24 hours with peaks up to +55°C

Conventional enclosed thermal current Ithe

Current (A)	Ambient temperature (°C)	Peak temperature (°C)	Additional requirements	No. of stages (from - to)	Mounting	Mounting size
20	35	40	Ambient temperature +35°C during 24 hours with peaks up to +40°C	--	--	--

Rated operational current Ie

Utilization category	Voltage (V)	Current (A)
AC-15	220 - 240	6
AC-15	380 - 440	4
AC-20A	690	20
AC-21A	20 - 690	20
AC-22A	220 - 500	20
AC-22A	660 - 690	16

Rated operational power

Utilization category	Voltage (V)	No. of phases	No. of poles	Power (kW)
AC-3	220 - 240	3	3	2,20
AC-3	380 - 440	3	3	3,70
AC-3	500 - 500	3	3	3,70
AC-3	660 - 690	3	3	3,70
AC-3	220 - 240	1	2	1,10
AC-3	380 - 440	1	2	1,50
AC-23A	220 - 240	3	3	3
AC-23A	380 - 440	3	3	5,50
AC-23A	500 - 500	3	3	5,50
AC-23A	660 - 690	3	3	5,50
AC-23A	220 - 240	1	2	1,50
AC-23A	380 - 440	1	2	2,20

Max. Fuse rating IEC

Fuse characteristic	No. of Fuses	Current (A)
gG	1	20

UL60947-4-1, UL508

Rated insulation voltage Ui

Voltage (V) AC / DC

300 AC

Rated thermal current

Current (A)	Ambient temperature (°C)	Additional Text
20	0 - 40	--

General Information

Text

- The operating handle and position indicating means to be used with these manual motor controllers should be provided from the manufacturer, or the operating handle and position indicating means to be used should have been previously evaluated in combination with the manual motor controllers.

General Information
Text

- When intended for use as a motor disconnecter the device shall be provided with a method of being locked in the OFF-position.

CSA

Rated insulation voltage Ui			
		Voltage (V)	AC / DC
		300	AC
Rated thermal current			
	Current (A)	Ambient temperature (°C)	Additional Text
	20	0 - 40	–

GENERAL TECHNICAL INFORMATION

Tightening torque of screws				
tightening torque (Nm)		tightening torque (lb-in)		
0,60		5		
Rated short-time withstand current Icw				
Time (s)		Current (A)		
1		130		
Size of conductor				
composition of conductor	Min. / Max. value	No. of conductor per terminal	Cross section (mm²) or (AWG/kcmil)	Material of the wire
Solid wire	Min.	1	0.5mm²	Copper
Solid wire	Min.	2	0.5mm²	Copper
Flexible wire	Min.	1	0.75mm²	Copper
Flexible wire	Min.	2	0.75mm²	Copper
Flexible wire	Max.	1	AWG 12	Copper
Flexible wire	Max.	1	2.5mm²	Copper
Single-core or stranded wire	Max.	1	AWG 12	Copper
Single-core or stranded wire	Max.	1	2.5mm²	Copper
Flexible wire with ferrule according to DIN 46228	Max.	1	2.5mm²	Copper
Flexible wire with ferrule according to DIN 46228	Min.	1	0.5mm²	Copper
Flexible wire with ferrule according to DIN 46228	Min.	2	0.5mm²	Copper

Approbations	Marking
Specification	

CE marking



UK Directives

IEC 60947-3; EN 60947-3; VDE 0660 Teil107

IEC 60947-3
EN 60947-3

UL 60947-4-1; CSA C22.2 No. 60947-4-1



CSA C.22.2 No.14



Power loss per pole	Power (W)
	0,90

Conditions during transport and storing	Minimum temperature (°C)	Maximum temperature (°C)	additional requirements
	-40	85	In case of temperatures below -5°C no shock load permissible

Shock / Vibration	Type of oscillation	Values
Resistance to vibration		IEC 61373 (1999) Category 1, Class B

General Information
Text

- Use only copper wires with or without tinned/silver-plated individual wires. Soldering the end of the wire before wiring is not allowed.
- Terminals with factory fitted jumper links are tightened during production for loss prevention. When opening the terminal clamps, make sure that no factory fitted links get lost and that all wire connections are properly seated.
- After wiring, ALL terminal screws must be tightened to the specified torque values.
- The protection class of the selected mounting type may vary if optional extras are used.
- Do not lubricate or treat contacts.
- Switches may only be mounted, connected and set into operation by qualified persons according to the accepted rules of technology.



General Information		
Text		
- After installation of the switches the spacings between the terminals must be sufficient to fulfill the requirement of the applicable standards.		
Operating temperature		
	Min. Temperature [°C]	Max. Temperature [°C]
	-25	55